

PT-928 Submersible liquid level transmitter

Description:

PT-928 submersible liquid level transmitter adopts the diffused silicon pressure sensor core of an internationally renowned company, and converts the depth of the measured liquid into 4~20mA through a high-reliability amplifier circuit and precision digital temperature compensation and nonlinear correction technology., 0~10VDC analog signal and IIC, RS485 and other standard digital signals. Fully sealed 304 stainless steel structure, protection grade IP68. Users can measure the height of various liquids conveniently, quickly and accurately. The ultra-high cost performance can be widely used in petroleum, chemical industry, metallurgy, electric power, complete water supply and other fields.

Product Features:

The high-performance diffused silicon sensor core is equipped with a highly integrated bridge pressure sensor signal conditioning advanced chip

Digital temperature compensation and nonlinear correction

A variety of signal outputs, equipped with breathable cables: perfect solution to the gauge pressure error that the sensor is not connected to the atmosphere

High sensitivity, high precision, high stability

Temperature compensation in all temperature zones, good electrical performance and long-term stability



The liquid inlet is equipped with a protective cover, which is convenient for cleaning and can effectively protect against sand, gravel and sediment

Can be customized according to customer needs and OEM OEM/laser marking

High cost performance, one year warranty

Specifications:

Measuring				
range	0-1000meters			
Overload	200%FS			
pressure				
Process	M20*1.5			
connection				
Accuracy	±1%、±0.5%、±0.2%、±0.1%			
Temperature	±0.03%/°C			
drift				
Temperature	-10∼70°C			
compensation				
range				
Long-term	±0.3%FS/year			



Shenzhen Ould Instrument Product Manual

	Onchi	Lilon Outu	THIS CT UNIOTIC T	T Oddoc III	anaa i	
stability						
Working	-40~85°C					
temperature						
Storage	-40~125°C					
temperature						
Output	absolute	ratio	4-20mA	IIC	RS485	
Signal	0-10V	0-5V				
Power supply	10-36	3.0-5.5	10-36	3.3-5.5	10-36	
Load (Ω)	>10K	>10K	≤50	-	_	
			(U-10)			
Ingress	IP68	Sealing	Nitrile rubber			
protection		ring				
Medium	Various fluids without corrosion					
adaptability						
Vibration	10gRMS, (20~2000)Hz					
Shock	100g, 11ms					
Insulation	Greater than 100MΩ @250VDC					
Response	Less than 1ms					
time						

CE Approval

EMC: IEC61326-1 B type


Electrostatic discharge immunity: IEC61000-4-2

Electromagnetic field immunity: IEC61000-4-3

EFT immunity: IEC61000-4-4

Surge immunity: IEC61000-4-5

Dimensions (in mm):



Electrical Connection:

Output definition	4∼20mA	Vout	IIC	RS485
Φ	Vin (Red)	Vin (Red)	Vin (Red)	Vin (Red)
0	GND	GND	SCL	A
	(Black)	(Black)	(White)	(Yellow)
3		Vout	SDA	B (White)
		(White)	(Yellow)	
Ф			GND	GND
			(Black)	(Black)

Selection tips:

- 1. When selecting the model, please note that the measured medium should be compatible with the part of the product in contact with the medium, and the specific gravity of the measured medium should be indicated (default is water $1g/cm^3$, $T=4^{\circ}C$).
- 2. There are various ranges of voltage input and output, which need to be specified in the order.
- 3. The IIC output type has no polarity protection. The installation and use process must be confirmed before powering on. The line length is less than 3 meters.
- 4. The cable should not be bent vertically during installation, but should be bent in a circular arc to avoid blocking the air guide hole and affecting the accuracy.
- 5. When measuring the flowing liquid, a hard pipe of about ϕ 50 can be inserted into the liquid, and several small holes are opened at different heights in the opposite direction of the water flow of the pipe to avoid the influence of liquid flow on the pressure.
- 6. When the product is installed in areas with frequent thunderstorms, it is recommended that users install lightning protection devices.
- 7. For special requirements, please negotiate with our company and indicate them in the order.